

## Transmit path L-band + reference link


- Suitable for all modulation formats
- Ultra-wide dynamic range
- Negligible intermodulation
- SNMP and web interface for remote monitoring and control
- Multiple carrier transmission


# RF + reference over a single fibre

The *ViaLiteHD* L-band + reference link is designed for applications where remote equipment shares a common frequency reference – typically 10MHz – however the link will support reference signals in the range 5-20MHz.

- Reference and traffic signals are transported on different wavelengths to minimise intermodulation
- Requires only a single fibre
- Reference can be supplied on a single RF connection with the carrier signal or from separate input sources
- A multiplexed signal can be connected to the BUC/amplifier or demultiplexed and supplied to two separate RF connections
- · Receive path link also available







ViaLiteHD fibre optic links are available as rack mounted cards, small form factor modules and Edge OEM modules.

A fully populated 19" 3U ViaLiteHD rack supports up to 26 links and accepts 13 RF cards plus an SNMP card and dual power supply modules. A 1U chassis accepts three RF cards or two RF cards plus an SNMP card.

Small form factor modules offer a compact, single link solution and Edge OEM modules allow system integrators and equipment manufacturers to build RF/optical interfaces into their own design. A range of support modules and accessories including indoor rack equipment and weatherproof outdoor enclosures is also available.

ViaLiteHD Transmit\_Path\_L-band\_+\_Reference\_Link\_Datasheet\_HRx-Kx-DS-2.docx

CR3206

01/05/14

#### **RF Performance Characteristics**

	L-Band	Reference
Impedance	50 ohms, duplexed	
Frequency range	950 - 2150 MHz	5-20 MHz
Flatness	± 1.5 dB (max) <sup>a d</sup> ± 0.5 dB (typical) <sup>a d</sup> ± 0.2 dB in any 36 MHz <sup>a t</sup>	± 0.5 dB (typical) <sup>a d</sup>
VSWR (50 Ohm)	1:1.5 <sup>t</sup>	
IMD	-62 dBc <sup>t c</sup>	-
CNR	57 dB <sup>1 b</sup>	-
Test input / output signal	-20 dBm	0 dBm
Maximum input power	+15 dBm (without damage)	
Gain stability	0.25 dB over 24 hours	
RF link gain (nominal)	+9 dB <sup>a</sup>	0 dB <sup>a</sup>
Input IP3(at default gain)	+12 dBm <sup>t c</sup>	-
P1dB (at default gain)	0 <sup>t</sup> dBm	+10 dBm
Noise figure(at default	20 dB <sup>t a</sup>	34 dB <sup>t a</sup>
LNB power (optional)	Internal 13/18V @ 700mA, with switchable tone	
SFDR	110 dB Hz 2/3 <sup>t a</sup>	-
Reference sidebands	55 dBc <sup>t</sup>	-

L-Band	Reference			
L-Ballu	1101010100			
75 ohms, duplexed				
950 - 2150 MHz	5-20 MHz			
± 1.5 dB (max) <sup>a d</sup> ± 0.8 dB (typical) <sup>a d</sup> ± 0.2 dB in any 36 MHz <sup>a t</sup>	± 0.5 dB (typical) <sup>a d</sup>			
1:1.5 <sup>t</sup>				
-50 dBc <sup>tc</sup>	-			
55 dB <sup>t b</sup>	-			
-20 dBm	0 dBm			
+15 dBm (without damage)				
0.25 dB over 24 hours				
+3 dB <sup>a</sup>	0 dB <sup>a</sup>			
+12 dBm <sup>t c</sup>	-			
0 dBm	+4 dBm			
22 dB <sup>t a</sup>	34 dB <sup>t a</sup>			
Internal 13/18V @ 700mA, with switchable tone				
109 dB Hz 2/3 <sup>t a</sup>	-			
50 dBc <sup>t</sup>	-			


### **Optical Performance Characteristics**

	L-Band	Reference		
Laser type	DFB	DFB		
Optical wavelength	1550 nm ± 20 nm	1310 nm ± 20 nm		
Optical power output	3.5 dBm (nominal)	3.5 dBm (nominal)		
Optical connector	SC/APC (E2000/APC and FC/APC options)	SC/APC (E2000/APC and FC/APC options)		


### **Temperature Characteristics**

	L-band + 10MHz Link	
Operating temperature	-20℃ to +50℃	
Storage temperature	-40℃ to +70℃	

### **Part Numbering and options**



#### **Mechanical Dimensions**



Email: sales@vialite.com Web: www.vialite.com



**UK Office** 65 Shrivenham Hundred Business Park, Watchfield, Swindon, SN68TY, UK +44 (0)1793 784389

North America Office 820 11th Street West Bradenton, Florida, 34205, USA +1 (855) 4-VIALITE

